

# Fender®

## Passport P500 Pro



Any time and any place you need big sound with great clarity and convenience, there's a new Passport PRO system by Fender that's right for you. Take a close look and listen, and we know you'll agree that Passport will take you places now as never before—Sound That Travels.

The new PRO models are the latest step in the ongoing evolution of Passport into the very finest in portable PA solutions. We've kept the best of previous Passport generations and added new features and improved functionality so that new Passport systems are ideal for whatever your application may be—education, sporting and worship events; meetings, seminars and presentations; gigs at parties, small clubs and coffeehouses. The eight-channel Passport 500 PRO is the new top-of-the-line Passport system. The 500 model has always had the most power and the best clarity; now it also has a port that lets you record your performance with CD quality (.wav) straight to a USB flash drive, CD-quality .wav and mp3 file playback, sub-out jack for an external powered sub-woofer, lighter weight (a full 9 lbs. lighter than the earlier Passport 500 model), smaller physical dimensions, and a redesigned speaker system with 10" woofer and improved clarity.

Product Type: Passport

Model Name: Passport® 500 Pro

Model

Number: 069-4405-940 (230V 50Hz) UK,

Description: Complete Self Contained Portable Sound System

Series: Passport

Dimensions: Height: 23" (58.42 cm)

Width: 29" (73.66 cm)

Depth: 11" (27.94 cm)

Weight: 44 lbs. (19.96 kg)

Covering: Black Luggage Style Molded Plastic Case

Power Output: 500 Watts Class-D Power Amp

Features: ♦ USB Port that lets You Record Your Performance with CD Quality (.wav) Straight to a USB Flash Drive,

♦ Six Mic Lines with XLR and 1/4" inputs,

♦ Two Stereo Inputs with 1/4" and 1/8" (for MP3 Player) Inputs,

♦ 1/4" Subwoofer Out with 120Hz High Pass Filter on Speaker Out,

♦ CD-Quality .wav and mp3 File Playback.

♦ Docking Connector for Passport Wireless Receiver

♦ Speaker Systems Feature Tightly Controlled Coverage to Minimize Feedback.

♦ 35mm (1-3/8") Stand Adapters are Built In to Each Speaker Cabinet

♦ Two Speaker Cables, and a Detachable Power Cable are Provided. (Mic / Cable Storage Compartment with Latching Lid.)

Specifications: ♦ 500 Watts Stereo, 250 Watts Continuous Power Per Channel Into 8 ohms

♦ Two Speaker Cabinets with One 10" Woofer and One 1.2" Horn Loaded Tweeter

#### MIXER SPECIFICATIONS:

Master Controls:

♦ Master Volume

♦ Level Meters

♦ Master Tone

♦ Reverb 1 / Reverb 2 Select Switch

♦ Reverb Time

♦ Reverb Tone

USB Record / Playback:

♦ USB Input

♦ Record

♦ Play / Pause

♦ Previous

♦ Next

Master Controls:

♦ Signal Present/Clip Indicator LED

♦ Level

♦ High / Low

♦ Reverb

♦ Pad (-20dB)

Mono Channel Inputs:

♦ Mic

♦ Line

♦ Phantom Power

Stereo Channel Inputs:

- ◆ 1/8" Stereo
- ◆ 1/4" Left (Mono) / Right

Front Panel Outputs:

- ◆ Stereo Out
- ◆ Level
- ◆ Pre Out / Power Amp In
- ◆ Sub Out

- ◆ Power/Protect LEDs

Rear Panel:

- ◆ Switchable Line Voltage for International Use
- ◆ On/Off Power Switch
- ◆ Power Socket
- ◆ Fuse
- ◆ Speaker Output Jacks